



## FEATURES

- Built in USB, FM and Bluetooth
- 3 microphone input and 2 AUX input
- AUX output and Pre-Output
- Built in Chime and Siren
- Built in EMC Input
- Suitable for high and low impedance speaker
- Running on both AC 240V and DC 24V

## DESCRIPTIONS

**EMIX EMDMA Series** mixing amplifiers have a wide range of output power ratings and enhanced cost effectiveness with three models: 60W, 120W and 250W. The mixing amplifier is integrated with FM tuner, USB and Bluetooth Playback. It is design to work with both high impedance (70V and 100V) and low impedance (4-16Ω). It is standard 19" rack-mountable with earpieces provided and only takes up to 2U of space.

## SPECIFICATIONS

MODEL	EMDMA-60	EMDMA-120	EMDMA-250
Power Supply	AC110-240V 50/60Hz		AC110-120V or 200-240V 50/60Hz
MIC 1 & 2 Sensitivity	10mV±1mv		
AUX 1 & 2 Sensitivity	350mV±50mv		
EMC IN Sensitivity	350mV±50mv		
MIC Frequency Response	120Hz~12kHz (±3dB)		
AUX Frequency Response	80Hz~15kHz (±3dB)		
Distortion	<1%		
Treble & Bass	10dB (±2)		
Rated Output	AC110-240V 60W	120W	250W
Power	DC24V	60W	
Port Output Voltage	4-16Ω,70V,100V(constant-voltage output)		
Machine Dimensions (D x W x H)	430×330×88mm		
Package Dimensions	500×500×165mm		
Net Weight	4.8KG	5.6KG	6.8KG
Gross Weight	6.3KG	7.1KG	8.3KG